

TRANSMITTER DIRECTED CODE DIVISION MULTIPLE ACCESS SYSTEM USING PATH DIVERSITY TO EQUITABLY MAXIMIZE THROUGHPUT

Background Of The Invention

I. Related Applications

The present application is a continuation of U.S. Patent Application No. 09/345,700, filed June 30, 1999 and assigned to the assignee of the present application.

II. Field of the Invention

The present invention relates to communication systems. More particularly, the present invention relates to a method and apparatus for determining to which user to provide access from among several users attempting to access a code division multiple access system.

III. Description of the Related Art

In accordance with several types of communication systems currently being used, access to the system is provided to one user at a time. Therefore, when a first user is granted access to the system, each other user must wait until the first user has released the system and access is granted to that user before he can use the system to communicate. Furthermore, in some such systems a scheduler is responsible for determining to which of the users access is to be granted. Each user applies to the scheduler for access to the system. The scheduler then selects from among the users that have submitted their applications.

In other systems, such as code division multiple access systems, access is granted to several users at once. In one such system, access is granted to users based upon several criteria. The first, and most important, criteria is to what type of service each user has subscribed. For example, in one such system, a user can request constant bit rate (CBR) service, variable bit rate

(VBR) service, or available bit rate (ABR) service. Users that pay for CBR service are guaranteed to receive service at an agreed upon data rate (i.e., bit rate). In contrast, if a user pays for VBR service, the user will be provided service at the rate necessary to transmit the particular information that is being sent. In such cases, the user's fees are typically calculated based upon the rates that were requested and granted to the user. If the user pays for ABR service, then the user will be granted access and a data rate will be assigned on an "as available" basis. Therefore, if there is sufficient capability in the system to provide access to an ABR user, then the ABR user will be granted access.

The capability of the system is typically dependent upon whether the amplifier in the transmitter is capable of transmitting the ABR user's information with sufficient power without overdriving the amplifier in light of the amount of power required by each of the CBR and VBR users' power requirements. The data rate at which the access will be granted will depend upon the amount of power that is available for transmitting the ABR user's data.

One example of an ABR user is an Internet Service Provider (ISP). Since customers of an ISP are able to tolerate delays and lower data rates, ISPs typically will opt for the less expensive ABR service. Even so, there are frequently situations in which there is insufficient power to transmit data for all of the ABR users that are requesting ABR service at any particular point in time. Therefore, the transmitting station must determine to which ABR users service is to be provided.

Several techniques are known for determining how to select the particular user to whom access to a system should be granted in a shared access communication system in which access is granted to only one user at a time or to less than all of the users requesting service. Access to the system is provided by one or more channels (i.e., air interface links between a common transmitting station and the user) to the user. Accordingly, each user is associated with at least one channel. In a CDMA system, each channel is associated with a unique CDMA code. Typically, the condition (i.e., quality) of the channel directed to each user will vary over time. Furthermore, the condition of the channels will vary from user to user. In some systems, access is granted to the user that can most efficiently use the system (i.e., the user associated with the best channel and thus able to receive data at the highest rate), thus maximizing the throughput of the communication system (i.e., amount of data

2025 RELEASE UNDER E.O. 14176

that can be communicated by the system within a predetermined amount of time). In other systems, access is granted such that each user will be provided with essentially equal access to the system when compared with the other users over a predetermined period of time. Equal access can refer to either the fact that each user gets an equal amount of time to communicate over the system, or that each user gets to transmit an equal amount of data over the system. Both the scheme in which the most efficient system user gets access and the scheme in which equal access is provided to each user are deficient. The scheme that focuses on maximizing throughput can lead to a situation in which some users receive little access to the system. In systems in which each user pays equally for access, this situation is unacceptable due to the resulting inequitable distribution of access. Likewise, in schemes in which each user is granted equal access regardless of the ability of that user to efficiently use the system, the throughput of the system suffers.

Accordingly, there is a need for a method and apparatus for determining to which user to grant access to a shared access communication system, such that the throughput of the system is maximized while ensuring that each user is granted equitable access to the communication system.

Summary Of The Invention

The disclosed method and apparatus is a transmitter directed, multiple receiver, communication system using path diversity. Path diversity is provided by the fact that at least some of the receivers are uniquely located with respect to others of the receives. Due to the differing paths, variations in the channel conditions of the channels will be uncorrelated. Therefore, at any particular time, some receivers will have a better instantaneous channel condition relative to the average condition of that channel.

The presently disclosed method and apparatus attempts to achieve two essentially competing goals in a system in which access is provided to less than all of the users at any one time. The first of these two goals is to equitably provide access to users of the communication system over "channels" (e.g., air interface links) between a common transmitting station and each user. The second of these two goals is to maximize the total amount of data

communicated through all of the channels of the communication system (i.e., system throughput).

The disclosed method and apparatus attempts to balance the two competing goals stated above by taking advantage of uncorrelated variations in the condition of each channel over time. In the simple case of two channels competing for access to the system, the times at which the channel conditions for the first channel are relatively high are essentially arbitrary with respect to the times at which the channel conditions for the second channel are relatively high. The presently disclosed method and apparatus takes advantage of this fact by attempting to transmit to the user associated with the channel that has the highest instantaneous channel condition relative to the average channel conditions for that channel. That is, by transmitting over the channel that has the greatest ratio of current conditions to average conditions, each channel will be used when it is at its best. If each channel is only used when it is at its best, the overall throughput of the system will be increased.

The determination as to which channel to select is made as follows. The common transmitting station transmits information to the users in time slots. A time slot is a period of time having a predetermined duration during which the common transmitting station transmits to a limited number of users. It will be assumed for simplicity that the common transmitter can transmit on only one channel at a time. Accordingly, for each time slot, the common transmitting station must select one channel. The instantaneous condition of the channel between a user and the common transmitting station is monitored by the user. An instantaneous channel condition indicator is communicated by the user to the common transmitting station for each time slot. The instantaneous channel condition indicator is a value representative of the condition of the channel during one time slot. The common transmitting station filters the instantaneous channel condition indicators associated with each channel to generate a filter output value for each channel at each time slot. In one embodiment of the disclosed method and apparatus, the filter function is defined such that a filter output value associated with each user and each transmission time slot represents the average throughput (i.e., average amount of data transmitted to that user over a period of time). Alternatively, the filter function is defined such that the filter output value represents an average of the channel condition of the

channel between the common transmitting station and the user associated with the channel.

In accordance with one embodiment of the presently disclosed method and apparatus, for each channel the value of the instantaneous channel condition indicator is compared to (e.g., divided by) the filter output value for that channel to generate an "access metric" for that channel. The access metric is a measure of the desirability of granting the user access relative to the desirability of granting each other user access. The common transmitting station uses the access metric to directly compare the desirability of granting access to any one channel with the desirability of granting access to each other channel. The user that has the greatest access metric is provided access to the channel.

In one embodiment of the disclosed method and apparatus, the filter output value is generated using a low-pass filter function to define a window in time over which the filter output value will be generated. A time constant of the filter reflects a "fairness time-scale" (i.e., the duration of the window in time). The fairness time-scale represents the duration of time over which it is desirable to have equitable access provided to each user. It should be understood that the fairness time-scale is dependent upon factors that include the type of data that is being transmitted to the users. For example, assume the transmission of Internet data to users attempting to gain access to the Internet. If each user receives an equitable amount of access to the system within one second, each user is likely to consider the access granting scheme to be fair, even if one user gets greater access for the entire beginning portion of the second. Accordingly, one second would be an appropriate fairness time-scale. In contrast, if the fairness time-scale were only one millisecond, then allowing one user access to the system for the first 100 milliseconds of the second would not be considered to be fair.

In one embodiment of the presently disclosed method and apparatus, the filter output value is updated only when the channel associated with that filter has been provided access. In the preferred embodiment of the presently disclosed method and apparatus, the filter output value is updated based on the rate at which that user received data. In this way, the filter output value reflects the average throughput to each user. This results in a built-in feedback mechanism that works to bias the selection of which user is to gain access. In accordance with this method and apparatus, when a user has been granted

access, that user will be automatically penalized when competing for access in the future.

Alternatively, in the case in which the filter output value represents the average channel condition, a bias is created by artificially increasing the access metric to compensate for the increase in the throughput to that user with respect to the users that did not received access during that period. The amount of this compensation may be fixed or may be proportional to the amount of data that was received during the last access. This allows the control of the average throughput to users to be weighted to favor those users that have received less data.

Details of the disclosed method and apparatus are provided in the detailed description that follows.

10067609.020402

Brief Description Of The Drawings

The features, objects, and advantages of the present invention will become more apparent from the detailed description set forth below when taken in conjunction with the drawings in which like reference characters identify correspondingly throughout and wherein:

FIG. 1 is a simplified block diagram of a communication system in accordance with the presently disclosed method and apparatus.

FIG. 2A is a graphical representation of the channel condition of a first channel and a second channel over time.

FIG. 2B is a graphical representation of the channel condition of a first channel and a second channel over time.

FIG. 3 is a simplified block diagram of a common transmitting station in accordance with the presently disclosed method and apparatus.

FIG. 4 is a functional block diagram of the functions performed by the processor.

Detailed Description Of Embodiments Of The Disclosed Method And Apparatus

Functional Overview

FIG. 1 is a simplified block diagram of a communication system 100 in accordance with the presently disclosed method and apparatus. The system 100 includes a common transmitting station 102 and a plurality of users 104. In FIG. 1, four such users 104 are shown. However, it will be understood by those skilled in the art that any number of users 104 may be included in the system 100. Furthermore, in cases in which one or more of the users 104 are mobile, the number of users 104 in the system may vary over time. Each user 104 can be considered as a receiving element of a distributed receiver that includes all,

or some, of the users 104. However, the users 104 of the presently disclosed method and apparatus need not combine, or provide to a common end user, the data that is received by each user 104. Accordingly, the users 104 may also be considered to be completely independent.

Each user 104 is capable of communicating with the common transmitting station 102 over an associated channel 106. For example, as shown in FIG. 1, a first user 104A receives transmissions from the common transmitting station 102 over an associated channel 106A. However, it should be noted that each user 104 may receive communications from the common transmitting station 102 over more than one associated channel 106. Such additional channels may exist as channels that use different frequencies, antennas, etc. In addition, such additional channels may exist due to multiple propagation paths between the common transmitting station 102 and the user 104. However, in the preferred embodiment of the disclosed method and apparatus, multiple propagation paths for the same signal are combined and treated as a single channel 106.

In one embodiment of a system in which the disclosed method and apparatus may be used, the common transmitting station 102 transmits signals to users during time slots. Each time slot preferably has a predefined and equal duration. However, the duration of such time slots may vary to accommodate varying data rates or for other reasons. The common transmitting station 102 preferably only transmits to one user 104 during each time slot. However, in an alternative embodiment of the disclosed method and apparatus, the common transmitting station 102 transmits signals to more than one, but less than all, of the users 104 in each time slot. In either case, for each time slot, the common transmitting station 102 must determine to which user or users 104 signals are to be transmitted.

This document discloses a method and apparatus for determining to which user or users 104 the common transmitting station 102 shall transmit in a way that maximizes the amount of data to be transmitted to all users 104, while ensuring that each user 104 receives an equitable amount of data with respect to each other user 104 over a predetermined "fairness time-scale". An "equitable amount of data" means that essentially equal receive-capability ratios. The receive-capability ratio is equal to the amount of data transmitted over a channel relative to the data rate that the channel can support. However, the

10057503, 000000

disclosed method and apparatus can alternatively be adjusted to favor greater data throughput at the expense of providing more access to users using channels that can support higher data rates over the fairness time-scale.

In accordance with the presently disclosed method and apparatus, each user 104 preferably monitors the condition of the channel from the user 104 to the common transmitting station 102 and transmits an instantaneous channel condition indicator to the common transmitting station 102. Each instantaneous channel condition indicator is a value representative of the condition of one channel during one time slot. In one particular embodiment of the presently disclosed method and apparatus, the instantaneous channel condition indicators are values representing a desired rate at which data is to be transmitted to the user 104 by the common transmitting station 102. In one such embodiment, the instantaneous channel condition indicators are data rate request (DRC) messages. Such DRCs typically indicate the maximum data rate at which data can be transmitted over the channel 106 with a predetermined bit error rate (BER).

The maximum data rate for a particular channel 106 is indicative of the carrier-to-interference ratio (C/I) for the channel 106. Alternatively, each user 104 monitors and communicates the C/I directly. In yet another alternative embodiment of the presently disclosed method and apparatus, the user 104 communicates instantaneous channel condition indicators that provide the common transmitting station 102 with an indication of the condition (i.e., quality) of the channel 106 without direct reference to either C/I or data rates. For example, the user 104 may provide the common transmitting station 102 with an indication of the amount of interference received by the user 104 and the amount of loss in the channel 106 between common transmitting station and the user 104.

It should be clear to those skilled in the art that there are several parameters, characteristic values, etc., that can be communicated by the user 104 to the common transmitting station 102 in order to characterize the channel conditions. The particular parameter or characteristic that is transmitted is not significant to the functioning of the presently disclosed method and apparatus. However, in the preferred embodiment of the presently disclosed method and apparatus, the channel condition indicator is directly proportional to the data rate

10667605.000002

at which the common transmitting station 102 will transmit data to the user 104 if that user is granted access to the channel 106 in the next time slot.

FIG. 2A is a graphical representation of the channel condition of a first channel 106A and a second channel 106B over time. The channel conditions of the first channel 106A are represented by a line 201. The channel conditions of the second channel 106B are represented by a dotted line 203. From FIG. 2, it can be seen that the channel conditions for both channels vary significantly over time. Furthermore, at nearly every point in time, the second channel 106B has superior channel conditions as compared to the first channel 106A. This can be understood by referring to FIG. 1 which shows that user 104A, which receives the channel 106A, is farther from the common transmitting station 102 than is user 104B, which receives the channel 106B. The greater distance between the common transmitting station 102 and the user 104A results in greater attenuation of the signal being received from the first user 104A. This results in an average channel condition for the first channel 106A (represented by a line 205) that is greater than the average channel condition (represented by a dotted line 207).

It can be seen from FIG. 2A that the variations in the channel conditions of the two channels 106 are uncorrelated. Therefore, the times at which the channel conditions for the first channel are relatively high are essentially arbitrary with respect to the times at which the channel conditions for the second channel are relatively high. The presently disclosed method and apparatus takes advantage of this fact by attempting to transmit to a user 104 associated with a channel that has a relatively high instantaneous channel condition relative to the average channel conditions for that channel 106. That is, by transmitting over the channel that has the greatest ratio of current conditions to average conditions, each channel will be used when it is at its best. If each channel is only used when it is at its best, the overall throughput of the system will be increased. Therefore, in accordance with one embodiment of the presently disclosed method and apparatus, the particular channel over which data is to be transmitted in any one time slot is selected as a function of the instantaneous channel conditions relative to the average channel conditions. However, in the preferred embodiment of the presently disclosed method and apparatus, selection of the channel over which data is to be transmitted in each slot is based on a function of the instantaneous channel condition relative to the

10067509.000001

average data throughput of a channel. The particular functions are defined below.

It will be understood by those skilled in the art that granting access to a user associated with a channel 106 having the highest channel conditions relative to the average channel conditions for that channel would greatly increase the data throughput for channels that have greater variations in channel condition. However, when contrasted with the throughput provided by an access scheme that granted equal access time to each user, such a scheme would not increase the data throughput for channels that have relatively low variations in channel conditions.

This can be understood by analyzing the case in which a first user 104A is associated with a channel 106A that has relatively great variations in the channel conditions, while a second user 104B is associated with a channel 106B that has relatively small variations in the channel conditions. FIG. 2B is a graphical representation of the channel conditions of such a first channel 106A, and second channel 106B. A line 209 represents the channel conditions of the first channel 106A and a dotted line 211 represents the channel conditions of the second channel 106B. A line 213 represents the average channel condition of the first channel 106A and a dotted line 215 represents the average channel condition of the second channel 106B.

Assuming that over the selected fairness time-scale, the channel condition of the first channel 106A is greater than average for half the time and less than the average for half the time, the same amount of access time will be granted to both the first and second channels 106A, 106B. However, the first channel 106A will have greater throughput than it would have had if equal access time were granted to each channel arbitrarily (e.g., in round robin fashion). However, the second channel 106B would have nearly the same data throughput, since the variations in the channel condition of the first channel 106A would dominate the selection process at the common transmitting station 102. That is, during the times when the first channel 106A has a relatively high quality, the second channel 106B will have an average quality. Accordingly, the first channel will be selected. During those times when the first channel 106A has a relatively low quality, the second channel 106B will have an average quality, and so be selected.

In order to compensate for this characteristic, a preferred embodiment of the presently disclosed method and apparatus selects the channel over which data is to be transmitted in a way that allows some of the increase in throughput to be distributed to users 104 associated with channels that have relatively small variations in channel condition. The way this is accomplished is disclosed in detail below.

Details of Functionality

FIG. 3 is a simplified block diagram of a common transmitting station 102 in accordance with the presently disclosed method and apparatus. The common transmitting station 102 receives signals that include instantaneous channel condition indicators over an antenna 301. The antenna 301 is coupled to a transceiver front-end 303. The transceiver front-end includes well known conventional radio frequency (RF) components that allow the signal to be received and converted to a base band signal, such as a diplexer, down converters, filters, etc. The base band signal is then coupled to a demodulator 305. The demodulator 305 demodulates the base band signal to allow the instantaneous channel condition indicator information to be accessed. The instantaneous channel condition indicator information is then coupled to a processor 307. The processor 307 may be any programmable device, state machine, discrete logic, or combination of these (such as might be included within an application specific integrated circuit (ASIC) or programmable gate array) that is capable of performing the functions associated with processor 307.

FIG. 4 is a functional block diagram of the functions performed by the processor 307. As shown in FIG. 4, the processor 307 includes filter modules 401, access metric calculator modules 403, and a channel selection processor 405. It will be clear to those skilled in the art that each of the functions performed by processor 307 and depicted in FIG. 4 may be integrated into a single software or hardware module, or alternatively may be integrated into modules in any grouping desired. Accordingly, any group of one or more of the functions performed by the processor 307 may be performed by a single module. Nonetheless, for the sake of clarity, one filter module 401a and one metric calculator module 403a are shown to be associated with the instantaneous channel condition indicators received from one channel 106A,

such that there is a one-to-one correspondence between channels 106 and filter modules 401 and likewise between filter modules 401 and access metric calculator modules 403. The processing of only one channel 106A is described in detail to simplify this disclosure.

The processor 307 receives an instantaneous channel condition indicator indicative of the instantaneous condition of the channel 106A within the filter module 401a associated with that channel 106A for each time slot. The filter module 401a calculates a filter output value based upon the instantaneous channel condition indicators received over the channel 106A. In accordance with one embodiment of the presently disclosed method and apparatus, the filter performs a low pass filter function.

The low pass function can be performed using one of several filter functions. In accordance with one such filter function, the filter output value $F(t)$ is calculated as provided in the following expression:

$$F_k(t+1) = (1-1/t_c) * F_k(t) + 1/t_c * (ChC_k) \quad \text{Eq. 1}$$

where $F_k(t)$ is the current filter output value at time t for the k^{th} channel, t_c is a time constant of a low pass filter function provided by this expression, and ChC_k is the instantaneous channel condition indicator for the k^{th} channel. The time constant represents a "fairness time_scale". The fairness time-scale represents the duration of time over which it is desirable to have essentially equal amounts of data transmitted to each user. It should be understood that the fairness time-scale is dependent upon factors that include the type of data that is being transmitted to the users. For example, assume the transmission of internet data to users attempting to gain access to the internet. If each user receives essentially equal amounts of data over a duration of approximately one second, each user is likely to consider the access granting scheme to be fair, even if one user gets greater access for the entire beginning portion of a second. Accordingly, one second would be an appropriate fairness time-scale.

Alternatively, the low pass filter function used to generate the filter output value sums the instantaneous channel condition indicators received for a channel and divides the sum by the total number of such instantaneous channel condition indicators that were summed. This is shown in the following equation:

$$F(t+1) = \frac{1}{t_c} \sum_{j=(t+1)-t_c}^t ChC_k(j) \quad \text{Eq. 2}$$

However, in the preferred embodiment of the presently disclosed method and apparatus, the filter output value is the average data throughput. In this case, the filter output value is calculated as the average of the instantaneous channel conditions representing the channel condition during the time when the channel has been selected. Accordingly, the filter output value is calculated differently depending upon whether the channel 106A was selected in the last slot or not. The filter module 401a is preferably coupled to the channel selection processor 405. The channel selection processor 405 indicates whether the channel 106A was selected in the last slot. If so, then the filter output value is calculated by the following expression:

$$F_k(t+1) = (1-1/t_c) * F_k(t) + 1/t_c * (ChC_k) \quad \text{Eq. 3}$$

To have the filter output value represent the average throughput, the channel condition ChC must be proportional to the data rate. It can be seen from Eq. 3 that if the channel 106A was selected, the filter output value will be modified to become closer in value to the value representing the instantaneous channel condition at the time the value of the most recent instantaneous channel condition indicator was determined. Alternatively, if the channel 106A was not selected in the last slot, the filter output value is calculated by the following expression:

$$F_k(t+1) = (1-1/t_c) * F_k(t) \quad \text{Eq. 4}$$

If the instantaneous channel condition is proportional to the data rate to be used for the transmission to the user 104 over the selected channel 106, then the resulting filter output value will be the average data throughput filtered by a low pass filter having a time constant t_c .

It can be seen from Eq. 4 that whenever the channel 106A is not selected the filter output value decays at a rate determined by the time constant t_c . The updated value does not take into account the instantaneous condition of the

channel. The filter output value for the channel 106A will continue to decay, regardless of the condition of the channel, until the channel 106A is selected again. At that time, the filter output value will be updated using the instantaneous channel condition indicator (i.e., the instantaneous channel condition indicator value most recently received by the common transmitting station 102). In the case in which the instantaneous channel condition indicators are related to the rate at which data is to be transmitted over the channel 106A, the filter output value is a representation of the total throughput of the channel 106A. That is, Eq. 4 can be through of as a low pass filter function with a time constant of t_c applied to the instantaneous rate at which data is being transmitted on the channel. The result of the filtering is an average rate at which data is being transmitted over the channel for a period of time equal to the time constant t_c .

In an alternative filter designed to determine the average data throughput, for each slot in which the channel associated with the filter is selected, the low pass filter function sums the instantaneous channel condition indicators received for a channel and divides the sum by the total number of such instantaneous channel condition indicators that were summed. When the channel associated with the filter is not selected, the filter output value decays in accordance with Eq. 4.

It should be noted that in one embodiment of the presently disclosed method and apparatus, the initial value for the filter output value is equal to R_{\min}/N , where R_{\min} is the minimum value allowed for the instantaneous channel condition indicator, and N is the total number of users 104. However, any reasonable initial value may be predetermined for the filter output value.

In accordance with another embodiment of the presently disclosed method and apparatus, the filter output value is biased upward by a constant each time the channel associated with that filter output value is selected. One such method of biasing the filter output value is to add a positive constant value to the filter output value, or to multiply the filter output value by a constant greater than one, in addition to time constant t_c or any other adjustment to the value, whenever the channel associated with that filter output value is selected. Such a direct bias to the filter output value will increase the filter output value, and thus make it less likely that the channel associated with that filter output value will be selected in the next slot.

10667609.020402

Once calculated, the filter output value is coupled to the access metric calculator 403a together with the most recently received instantaneous channel condition indicator. The most recently received instantaneous channel condition indicator represents the instantaneous channel condition in the form of the C/I ratio of the channel, the instantaneous data rate, or any other such parameter that indicates the current quality of the channel.

The access metric is calculated as a function of the instantaneous channel condition and the average channel condition. Accordingly, in one embodiment of the presently disclosed method and apparatus, the access metric is calculated as a function of: (1) the C/I ratio of the channel and the filter output value; or (2) the instantaneous data rate and the filter output value. In other alternative embodiments of the presently disclosed method and apparatus, the access metric can be calculated as a function of any other measure of the instantaneous channel condition relative to the filter output value.

The filter output value is a function of either: (1) the average data rate, or (2) the average channel condition. Therefore, the access metric is, for example, a function of: (1) the average data rate and the instantaneous channel condition, (2) the average channel condition and the instantaneous channel condition, (3) the average data rate and the instantaneous data rate, or (4) the average channel condition and the instantaneous data rate. In accordance with one embodiment, the access metric calculator 403a divides the most recently received instantaneous channel condition indicator by the filter output value to calculate an access metric, AM.

$$AM = ChC_k/F_k(t) \quad \text{Eq. 5}$$

It can be seen that the value of the access metric is directly proportional to the instantaneous channel condition. The higher the instantaneous channel condition, the greater the access metric for that particular channel. The access metric is calculated for each channel based upon the filter output value calculated for each channel. The access metrics of all of the channels 106 are then directly compared by the channel selection processor 405 to determine

which channel 106 is to be selected for transmission in the next slot. The channel associated with the greatest access metric value is selected.

The channel selection processor 405 is coupled to each access metric calculators 403 via signal lines 407. Signal lines 407 couple information from the channel selection processor 405 to each filter module 401. The information indicates which channel 106 was selected for transmission in the next slot. The information may be in the form of a value indicating the particular channel 106 that was selected. Alternatively, the information may be a digital value indicating whether or not the receiving filter module 401 is associated with the selected channel. It should be understood that in the case in which the functions of the filter module 401, the access metric calculator, and the channel selection processor are all performed in one module, there may be no need for "signals" to be generated to indicate the results of each function. Alternatively, the results of one or more of the functions may be stored in a location accessible to one or more of the other functions.

Referring back to FIG. 3, the processor 307 outputs information indicating which channel 106 has been selected on a signal line 309 to a data multiplexer/channel selector 311. Several data lines 313A, 313B, 313C, 313D provide data to the data multiplexer/channel selector 311. Each of the data lines provides data that is to be transmitted to one of the users 104. In response to the signal provided on the signal line 309, the data multiplexer/channel selector 311 selects one of several data streams to be coupled to the transceiver front end 303. The selected data stream is coupled to the transceiver front end over a signal line 315. In accordance with the preferred embodiment of the presently disclosed method and apparatus, the transceiver front end 303 transmits the information received on signal line 315 to the user 104 associated with the selected channel 106 at a rate that is proportional to the most recent instantaneous channel condition indicator received from selected user 104.

Application to Concurrent Transmissions

In an alternative embodiment of the presently described method and apparatus, the common transmitting station 102 transmits signals to more than one user in each time slot. The common transmitting station 102 uses available power to first transmit signals to all of the constant bit rate (CBR) users and all

the variable bit rate (VBR) users for which the common transmitting station 102 has data. Alternatively, if additional power is available after transmission to CBR users, then the common transmitter transmits to all of the variable bit rate (VBR) users for which the transmitting station 102 has data. If, after transmitting to all CBR and VBR users, there remains available power for additional signals to be transmitted, the common transmitting station 102 transmits to available bit rate (ABR) users. If the total power required by all of the ABR users exceeds the available power, then the following scheme is used to determine to which ABR users the common transmitter will transmit. It should be understood that techniques can be used that allow a receiver to receive signals with less power than is necessary to decode the information transmitted in the signals without retransmission. In accordance with these techniques, power is accumulated over several repetitive transmissions (e.g., using R-rake receivers). Accordingly, the amount of power that is "required" will depend upon the number of times the common transmitting station will retransmit information.

In accordance with one embodiment of the presently disclosed method and apparatus, the common transmitter 102 determines an access metric based on the condition of the channel to each user and the "throughput". Throughput is defined as the amount of information that has been transmitted over a period of time. Accordingly, throughput can be associated with one or more users. The throughput associated with a particular user is the amount of information that has been transmitted to that user. The throughput of the system is the total amount of information that has been transmitted to all users.

Throughput is preferably determined for each user by applying a filter function as follows:

$$T_k(t+1) = (1-(1/t_i))T_k(t) + (1/t_i) R_k(t) \quad \text{Eq. 6}$$

where $T_k(t)$ is the throughput at time t for the k^{th} user, t_i is a filter time constant, and $R_k(t)$ is the rate at which data was last transmitted to the k^{th} user.

In accordance with one embodiment of the disclosed method and apparatus, if the common transmitter 102 has not transmitted to the k^{th} user in the last time slot, then $R_k(t)$ is equal to zero. Accordingly, if the common transmitter has not transmitted to the k^{th} user, then Eq. 6 reduces to the following equation for the k^{th} user:

$$T_k(t+1) = (1-(1/t_i))T_k(t) \quad \text{Eq. 7}$$

where $T_k(t)$ is the throughput at time t for the k^{th} user and t_i is a filter time constant.

Accordingly, a filter applies either Eq. 6 or Eq. 7 and outputs a filter output value associated with each user, each such value representing the throughput of a channel to a user. An instantaneous channel condition is determined for each channel between the common transmitting station 102 and each user. In one embodiment of the presently disclosed method and apparatus, the instantaneous channel condition for the channel to the k^{th} user is the carrier-to-interference (C/I) ratio for the channel to the k^{th} user. It will be understood by those skilled in the art that any one of several well known methods can be used to determine the value of C/I.

In one embodiment of the presently disclosed method and apparatus, the access metric is a function of C/I and throughput. In one such embodiment, the instantaneous channel condition of the channel to the k^{th} user is divided by the throughput (i.e., the filter output value for the k^{th} user) of a channel to the k^{th} user to generate an access metric. In another embodiment of the presently disclosed method and apparatus, the access metric is a function of the ratio of the instantaneous channel condition to the channel condition taken over time.

In the case in which the access metric is a function of the ratio of the C/I to the throughput, the access metric is used to determine to which ABR user, or users, information is to be transmitted in order to optimize the total system throughput while maintaining some level of "fairness" (i.e., essentially equitable system access) to all of the ABR users.

In one embodiment of the presently disclosed method and apparatus, a user may indicate to the common transmitting station 102 that a frame of data was not received or was received with more than a threshold number of errors. In this case, the throughput value associated with that user is preferably corrected to account for the fact that the data that was sent was not properly received. In accordance with one embodiment of the presently disclosed method and apparatus, the correction is made as follows:

$$T_k(\text{new}) = T_k(\text{old}) - (1/t_i)R_k(t) \quad \text{Eq. 8}$$

1000 JOURNAL OF CLIMATE

1000

1

Eq.9

having the five greatest access metric values with power being divided among the users in proportion to the access metric associated with each user. It should be understood by those skilled in the art that there is a large variety of ways by which selection of the number of ABR users and the rates at which information is to be transmitted to them can be made. A significant feature of the disclosed method and apparatus is that an access metric is used to assist in selecting to which, from among a plurality of ABR users, transmissions are to be made.

In some cases, a common transmitter 102 may not have data ready for transmission to the ABR user with the best access metric. In this case, the throughput value associated with that user can be adjusted in one of at least three ways. First, the throughput value can be adjusted as though data were to be sent to that user at the rate that would have been selected if information were available for transmission. Second, the throughput value can be left unadjusted for that time slot. Third, the throughput value can be adjusted in the same manner as if the user were not selected for transmission.

A number of embodiments have been described. Nevertheless, it will be understood that various modifications may be made without departing from the spirit and scope of the invention. Accordingly, it is to be understood that the invention is not to be limited by the specific illustrated embodiment, but only by the scope of the appended claims.

WE CLAIM:

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159